

Qing Camera Compatibility List (Cable Control)

Brand	Camera list	Camera version	Control cable	Function	Setting notes on Camera/Lens	HUB Firmware	
Canon	SD MarkV	1.1.2	USB 3.0 to Micro 3.0 (A02)	1.Take photos 2.Start/Stop recording video 3.Follow focus electronically	When using Follow focus electronically, the lens needs to be in MF mode	RT_HUB_V103	
	EOS 90D	1.0.0	USB 2.0 to micro (A01)				
	EOS 200D II	1.0.0					
	80D	1.0.2	USB 2.0 to mini (B01)				
	6D	1.1.8					
	SD MarkIII	1.3.5					
	6D MarkII	1.0.3					
	EOS R	1.0.0	USB 2.0 to Type C (C01)				Please turn off the WiFi connection for Cable control.
	EOS RP	1.3.0					
	GTX mark II	1.0.1					
	Mirror&2	1.1.0					
	EOS R5	1.1.1					
	EOS R6	1.1.1	1. Due to camera system, please switch the shooting mode to photo mode before taking photos. When shooting a video is needed, switch the shooting mode to movie mode. 2. For EOS R5/R6, shutter release can't be used to control video shooting in photo mode otherwise the camera will easily crash.				
	EOS SD5 R	1.1.9R	USB 2.0 to micro (A01)	1.Take photos 2.Start/Stop recording video 3.Switch Photo/ Video Mode	1.After connecting the cable, be sure to power on the Qing before the camera and wait for about 5 seconds for successfully connection after camera power on,the camera icon on the gimbal screen will light up. 2.When the camera is in photo mode and the gimbal switches to video mode, some keys of the camera will not respond to commands.	RT_HUB_V105	
	EOS SD MarkIV	1.2.1	USB 2.0 to micro (A01)	1.Take photos 2.Start/Stop recording video		RT_HUB_V105	
EOS R50	1.0.0	USB 2.0 to micro(A01)	1.Take photos 2.Start/Stop recording video 3.Follow focus electronically	1. when using the gimbal to control focus electronically, you may need to switch the lens between AF and MF to see which best fits your need. 2. When shooting timelapse video, please set the camera "Image Review" to be off.	RT_HUB_V105		
M50	1.1.0	USB 2.0 to micro(A01)	1.Take photos 2.Start/Stop recording video		RT_HUB_V105		
EOS R5C	1.0.0.1	USB2.0 to TypeC (C01)	1.Take photos 2.Start/Stop recording video 3.Follow focus electronically	1.After the gimbal and camera are turned on, you need to wait about 10 seconds to establish a connection 2.When the camera is in photo file, the gimbal can control taking and recording; 3.When the camera is in video file, the gimbal can control recording 4.When you look back at an image, you have to switch to photo, and when you look back at a video, you have to switch to video	RT_HUB_V105		

Sony	a7II	V2.00	Type-C to Multi	1.Take photos 2.Start/Stop recording video 3.Zoom/Half-press to focus	1. Can control motorized zoom lens to zoom. 2. Can only control digital zoom while using non-motorized lens. 3. Select "Network" and then turn off "Ctrl w/ Smartphone" in camera setting. 4. Set up the USB Connection to PC remote in camera setting menu.	RT_HUB_V101					
	a7RII	V4.00									
	a7R	V4.00									
	a9	V2.00									
	a7R	V2.00									
	a7 III (A7M3)	V3.00									
	a7R III	V3.01									
	a7R IV	V1.00									
	a6300	V2.00									
	a6400	V1.00									
	6100	V1.00									
	6400	V1.00									
	a6500	V2.00									
	ZV-1	V1.00									
A7 SII	1.01	USB2.0 to TypeC (C01)	1.Take photos 2.Start/Stop recording video	1. Can control motorized zoom lens to zoom. 2. Can only control digital zoom while using non-motorized lens.	RT_HUB_V104						
ZV-10	V1.00										
A7M IV	V1.00										
RX100 VI (RX100M7)	1.00										
A7R4	V1.20										
A7C	V2.00										
RX100V (RX100M4)	V2.00										
Nikon	D7500					1.00	USB 2.0 to Type C (C01)	1.Take photos 2.Start/Stop recording video 3.Zoom/Half-press to focus 4.Follow focus electronically	1. After connecting the cable, be sure to power on the Qing before the camera. 2. Please set [Zoom Setting] to be "Clearance Zoom" or "Digital Zoom" to enable Digital Zoom. 3. Please set [Auto Review] to be "OFF" when shooting the timelapse video;	RT_HUB_V105	
	Z7					1.00					
	Z6					2.00					
	D850					1.01					
	Z5					1.00					
	Z50					1.00					
	Z6 II					1.21					
	Panasonic	GHSx	V1.2	Panasonic Shutter Cable Type C to DC2.5	1.Take photos 2.Start/Stop recording video 3.Follow focus electronically	1. Please set the [Ctrl w/ Smartphone] to be off. (Network) → [Ctrl w/ Smartphone] → [OFF] 2. Set "USB Connecting" to be "PC Remote". (Network) → [PC Remote Function] → [PC Remote] → [On] 3. Set "Still Img. Save Dest." to be "Camera Only". (Network) → [PC Remote Function] → [Still Img. Save Dest.] → [Camera Only] 4. After connecting the cable, be sure to power on the Qing before the camera. 5. Please set [Auto Review] to be "OFF" when shooting the timelapse video 6. Switch photo or video (P A S M AUTO mode support)					RT_HUB_V105
		GH4	V2.7								
		LUMIX G9	V2.0								
		S1H	V2.0								
		S5	V2.0								
		GH5	V2.6								
		GH5	V2.6								
GH6		V1.2									
GH6		V1.2									
FUJIFILM		XT-200	V1.02				Type-C to TRS1.5 (T03)	1.Take photos 2.Start/Stop recording video 3.Half-press to focus	1. Please set up "MIC/REMOTE RELEASE" to REMOTE, Steps: Press Menu, Video Setting } MIC/REMOTE RELEASE } REMOTE 2.To control recording, you need to turn the camera to video mode .	RT_HUB_V101	
		X5-10	V1.02								
		X-43	V1.22								
		X-A5	V1.00								
		X-T30 II	V1.00								